

Notice



- ☐ CORRECTION
 ☒ PRODUCTION CHANGE
☐ SERVICE FLASH
 ☐ ADD INFORMATION

FILE NO.

REVISION 0

Please add this notice to the Service Manual listed below.

Category: **COLOR TELEVISION** Date: **OCTOBER / 26 / 2009**
 Model: **DP42849** Effective from : Chassis No. **P42849-04**
 Destination: **U.S.A. / CANADA** REF : **No. SM780157-04**

NOTE: Match the Chassis No. on the unit's back cover with the Chassis No. in the Service Manual. **If the Service Manual Chassis No. does not match the unit's**, additional Service Literature is required. This chassis is similar to Chassis No. P42849-00. Only the **difference** Service Information is given in this manual. For detailed Service Information, refer to the **Original** Service Manual and **Notices** for Chassis No. PP42849-00 used in Model DP42849 (SM780157).

SERVICING SHOULD BE PERFORMED BY ONLY TRAINED AND QUALIFIED SERVICE PERSONNEL.

1. IN THE SERVICE ADJUSTMENTS

PAGE 4 ON-SCREEN SERVICE MENU

Item No. **088 OP2 Data** should be changed from **24h** to **26h** in the table and in Note 2.

2. IN THE CHASSIS ELECTRICAL PARTS LIST MISCELLANEOUS

The reason for change.

- A : Misprint B : Quality Reliability C : Standardization
 D : Design E : Add as a possible sub F : Schematic location change
 G : Purchasing Request

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 9, Chassis Electrical Parts List	C1652	Old	CEXLB1C102VDN	ELECT 1000U M 16V	1	NO	D
		New	N/A	NOT USED	0	NO	
	C1691	Old	N/A	NOT USED	0	NO	D
		New	CK1H104KLZBNG	CERAMIC 0.1U K 50V	1	NO	
	C1692	Old	N/A	NOT USED	0	NO	D
		New	CK1H102KLZBNG	CERAMIC 1000P K 50V	1	NO	
	C1700	Old	N/A	NOT USED	0	NO	D
		New	CK1H104KLZBNG	CERAMIC 0.1U K 50V	1	NO	

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 9, Chassis Electrical Parts List	C1702	Old	N/A	NOT USED	0	NO	D
		New	CEXLB1C102VDN	ELECT 1000U M 16V	1	NO	
	C1704	Old	N/A	NOT USED	0	NO	D
		New	CEXLB1V471VDN	ELECT 470U M 35V	1	NO	
Page 12 Chassis Electrical Parts List	D0002	Old	N/A	NOT USED	0	NO	D
		New	DD1SS352----G	DIODE 1SS355-TE-17	1	NO	
	D1701	Old	N/A	NOT USED	0	NO	D
		New	DDSS3P3-E3--G	DIODE SS3P3-E3/84A	1	NO	
Page 12 Chassis Electrical Parts List	IC1690	Old	N/A	NOT USED	0	NO	D
		New	QXXAVD055---P	IC XC61CN4202MR	1	NO	
	IC1700	Old	N/A	NOT USED	0	NO	D
		New	QLA5774MPE--P	IC LA5774MP-DL-E	1	NO	
	L1604	Old	1LB4L26B0740G	INDUCTOR, 220 OHM	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 13 Chassis Electrical Parts List	L1686	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1687	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1692	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1750	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1751	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1752	Old	N/A	NOT USED	0	NO	D
		New	1AV4L2WK560MN	INDUCTOR, 56U M	1	NO	
	L1753	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1754	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 13, Chassis Electrical Parts List	L1755	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1756	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1757	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	Q1701	Old	N/A	NOT USED	0	NO	D
		New	T2SC3928A1R-P	TR 2SC3928A1S	1	NO	
	R017	Old	RGF4700JT CANL	MT-GLAZE 470 JA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 15, Chassis Electrical Parts List	R018	Old	N/A	NOT USED	0	NO	D
		New	RGF4700JT CANL	MT-GLAZE 470 JA 1/10W	1	NO	
	R027	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZT CANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R1607	Old	RGFR000ZT CANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 16, Chassis Electrical Parts List	R1690	Old	N/A	NOT USED	0	NO	D
		New	RGF1002JT CANL	MT-GLAZE 10K JA 1/10W	1	NO	
	R1691	Old	N/A	NOT USED	0	NO	D
		New	RGF1002JT CANL	MT-GLAZE 10K JA 1/10W	1	NO	
	R1692	Old	N/A	NOT USED	0	NO	D
		New	RGF2202JT CANL	MT-GLAZE 22K JA 1/10W	1	NO	
	R1693	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZT CANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R1694	Old	N/A	NOT USED	0	NO	D
		New	RGF4701JT CANL	MT-GLAZE 4.7K JA 1/10W	1	NO	
	R1700	Old	N/A	NOT USED	0	NO	D
		New	RGF2202JT CANL	MT-GLAZE 22K JA 1/10W	1	NO	
	R1701	Old	N/A	NOT USED	0	NO	D
		New	RGF47R0JT CANL	MT-GLAZE 47 JA 1/10W	1	NO	

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 16, Chassis Electrical Parts List	R1702	Old	N/A	NOT USED	0	NO	D
		New	RGF3900FTCANL	MT-GLAZE 390 FA 1/10W	1	NO	
	R1703	Old	N/A	NOT USED	0	NO	D
		New	RGF8201FTCANL	MT-GLAZE 8.2K FA 1/10W	1	NO	
	R1704	Old	N/A	NOT USED	0	NO	D
		New	RGF1001FTCANL	MT-GLAZE 1K FA 1/10W	1	NO	
Page 15, Chassis Electrical Parts List	R840	Old	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R843	Old	N/A	NOT USED	0	NO	D
		New	RGF4701JTCANL	MT-GLAZE 4.7K JA 1/10W	1	NO	
Page 20, Chassis Electrical Parts List	▲ U901	Old	1AV4U20C39200	UNIT, POWER	1	NO	D
		New	1AV4U20C17401	UNIT, POWER	1	NO	

For parts or service contact:

Sanyo Manufacturing Corporation
P.O. Box 2000
3333 Sanyo Road
Forrest City, Arkansas 72335-2000